

UPS

LAPTOP UPS/POWERBANK LAL-22400C



www.lalelaretail.co.za

 Lalela



INPUT:

INPUT VOLTAGE: 29.4V DC
INPUT CURRENT: 1.5A

Size: 160x82x22mm

PD Output: 60W Max.
5V/3A 9V/3A 12V/3A 15V/3A
20V/3A



Output: 24V/3A
Input: 29.4V/1.5A

Output: 19.5V/3A

Output: 5V/2.4A 12W

SPECIFICATIONS:

Model: LAL-22400C

Capacity: 82,880mAh

Built-in battery: High quality lithium-ion batteries

OUTPUT:

OUTPUT VOLTAGE DC: 19.5V/3A & 24V/3A

OUTPUT CURRENT: 3A

USB-A: 5V/2.4A 12W Max.

USB-C PD: 5V/3A 9V/3A 12V/3A 15V/3A
20V/3A

HOW TO CHARGE THE POWER BANK?

When the LED indicator of the AC-DC charger shows red, the charging process is in progress. When the LED indicator of the AC-DC charger shows green, the charging process is complete and the power bank is fully charged.

Note:

1. Please don't use any other chargers to charge the power bank.
2. In order to use the USB / Type C or USB Type A port – please turn on the device using the power button on the side. You do not need to turn on the device in order to use the DC ports, they will turn on automatically once a cable is detected.
3. Only use one of the four output ports (DC1, DC2, USB-A and USB-C) to discharge at a time.

PACKAGE CONTENT

1 x Power bank
1 x DC Cable
1 x 29.4V/1.5A AC/DC Charger
1 X USB Type-C Cable
12 x Laptop Connectors



Charger



DC Cable



Laptop Connectors

M Lenovo
FOR HP 4530 4.5*3.0 HP
FORDELL 7406 DELL
FOR HP 7406 HP
H 5.0*10 Samsung
H 35135 3.5*1.35 Sharp,DELL
G 4017 4.1*7 Acer, Acer, SONY
F 4817 4.8*1.7 HP,In,Compaq, Asus
E 5817 5.8*1.7 Acer, SONY
C 5525 5.8*2.5 Lite Fujitsu, Dell
B 6330 6.3*3.0 Toshiba
A 6014 6.0*1.4 SONY,Fujitsu

CONTACT US

For any inquiries or comments concerning our product, or any quality-related issues with our product, please feel free to contact us.

We will respond to you as soon as possible and do our best to assist.

Email us: support@lalelaretail.co.za

Website: www.lalelaretail.co.za



 tech support:
support@lalelaretail.co.za

 Lalela

CAUTIONS

1. The product should be protected from exposure to water, and heat.
2. The product should be stored in a cool, dry space indoors where it is safe from exposure to water and heat.
3. Do not leave the product in a low voltage state for an extended period of time. Charge fully every 3 months to extend the battery capacity.
4. Do not immerse the product in water or other liquids.
5. Do not modify or disassemble the product.
6. Do not reverse connect the input or output.
7. Do not let children play with this product.
8. Do not put the product into fire or extreme heat.
9. Do not place heavy objects on the product, and the product should not be thrown.
10. If any liquid discharges from the product gets into your eyes, do not rub your eyes, rinse with water and consult a doctor immediately.
11. If there is any abnormal activity or malfunction while charging, please contact your dealer.


Lalela